

Programming Manual – Chargingterminal PAX S80



Note: The chargingterminal must be operated with caution. If the station is shaken, the operating system may be deleted as the charging station is subject to the regulations of a credit card reader.

Programming:

- Plug the power supply together and connect it to the table charging station.
- Place the enclosed paper roll with an arrow up in the designated opening
- To turn on the table charging station, press the red button.
- Press "Menu" button -> confirm with "enter".
- Move up and down with arrow keys in the menu.
- 01 Decimal places -> enter -> Select decimal places with arrow keys and confirm them with enter (e.g. € = 2 decimal places, PLZ = 2 decimal places, HUF = 0 decimal places)
- 02 Currency -> enter -> Select currency and confirm with enter. (If no currency fits, select option 01)
- 03 Purse Function -> enter -> Use arrow keys to "02 Increment" and confirm with enter.
- 05 Ticket -> enter -> Select "01 On Request" with arrow keys and confirm with enter.
- 09 Max Key Credit -> enter -> with "CLEAR" delete amount and type in the amount according to currency list and confirm with enter. (e.g. € = 500.00; PLZ = 500.00; HUF = 9999; RON = 500.00; RSD = 9999)
- 10 Administrator -> enter -> Use arrow keys to "configure" -> enter -> enter 3-digit number -> enter -> enter 4-digit number -> enter -> enter 4-digit number -> enter

The administrator code consists of the CarWash key code of the attachment. This is on every key reader and on the currency list. For example, a code looks like this: 103-1052-1000.

Important: The 3-digit number becomes the code for access to the menu of the table loading station. Never forget this one.

Press "Cancel" to come back to the main menu.

- 12 Merchant Data -> enter -> Select "VAT" with arrow keys and confirm with enter. Now enter the VAT rate here and confirm it with enter. With "Cancel" back to the main menu.
- 16 Language-> enter -> Use arrow keys to select language and confirm with enter.
- 22 ADD Application -> enter -> 01 Configuration -> enter -> 02 Always -> enter -> With "Cancel" back to main menu.
- 14 Configuration -> enter -> Use arrow keys to "print" and confirm with enter. With "Cancel" back to the main menu.
- 10 Administrator -> enter -> Use arrow keys to choose „print“ and confirm with enter. Press “Cancel” 2x to get to the main menu.

End of programming